

UTS101-I USB to Serial Port Converter

◆ **Support one Ground Isolated RS232 port**

◆ **Safety and Less Expensive**



- ★Support **USB2.0** device controller
- ★**512 Bytes FIFO** for data transfer
- ★Support **LED display** for each port
- ★one **Ground Isolated RS232** port for safety connection.
- ★Support **bus powered** mode
- ★Use ASIX MCS7810 chip

UTS101-I Specification :

USB interface:

- *Connector type: USB B type connector.
- *Device Controller: USB 2.0
- *stream FIFO size: 512Byte per serial port.

RS232 interface:

- *Connector type: DB9 male connector.
 - *Number of ports: 1
- NOTE: support GROUND Isolated feature
between USB connection and RS232
connection

LED indicator:

- *PWR: DC power input ON indicator.
- *Serial1: port 1 TXD/RXD signal activity.

Power input:

- *USB bus powered mode.
- *Current consumption: 200mA @ 5VDC.

Environment :

- *operating temperature: 0℃ to 55 .℃
- *operating humidity: 10% to 95% RH.
- *storage temperature: 0℃ to 65℃.
- *storage humidity: 5% to 95% RH.

Dimension :

- *UTS101-I box:
92mm (W) * 118mm (L) * 27mm(H)

Performance upgrade capability and relative products :

- *UTS134i box: USB to four ground isolated RS422/485 ports safety model.
- *UTS112 box: USB to two RS232/RS422/RS485 port cost effective model.
- *UTS111 box: USB to one RS232/RS422/RS485 port cost effective model.
- *UTS131-I box: USB to one ground isolated RS422/RS485 port.
- *UTS102-I box: USB to two ground isolated RS232 ports.
- *UTS112-I box: USB to two ground isolated RS232/RS422/RS485 ports.
- *UTS400 box: USB to four RS232 ports cost effective model.
- *UTS040 box: USB to four ground isolated RS232 ports safety model.
- *UTS004 box: USB to four ground isolated RS422/RS485 ports safety model
- *UTS485 box: USB to two RS232 and two ground isolated RS422/485 ports.

***All names are the trademarks of their respective organization.



RAYON TECHNOLOGY CO., LTD.

2F, No. 177, Chung_Shan 2 Rd., Lu_Chou, New Taipei city, Taiwan,R.O.C.
TEL: 886-2-82858362 FAX: 886-2-82857065
E-Mail: rayon@ms1.hinet.net or info@rayontech.com.tw
WEB: <http://www.rayontech.com.tw>