# APE85/2 Advanced PCIe Card

# PCIe Bus Eight Port Card RS422 / RS485 selectable



- ★Each port can set to RS422/RS485 by DIP Switch
- ★Support ADDC feature in RS485.
- ★Suitable for Windows 2000/XP
- ★Suitable for WIN7/8/10

## APE8S/2 (APe138) Specification:

#### Serial Communication Controller:

\*type: ASIX MCS9865

#### Hardware compatibility:

\*PCIe bus slot.

#### Software compatibility:

- \* Windows 2000/XP.
- \* Windows Vista.
- \* WIN7/8.
- \* WIN10.

#### Dimension:

- \*APE8S/2 (Ape138)card: 142 \* 110 mm.
- \*APE8S/2 model with standard PCIe bracket.

#### System I/O & IRQ mapping:

- \*I/O mapping assigned by PCI BIOS.
- \*Memory mapping assigned by PCI BIOS.
- \*three IRQ mapping assigned by PCI BIOS.

#### Port capability:

- \*number of port: 8 ports per card.
- \*Interface: RS422/RS485.

Note: Each port can set to RS422/RS485 by DIP switch.

- \*Baud Rate: each port can be configured to 50--115200bps.
- \*Connector type: DB62 female connector.
- \*R804 cable support DB62 male to eight DB9 male connector.
- \*R801 cable support DB62 male to eight DB25 male connector.

#### **Environment**:

- \*operating temperature : 0°C to 55°C
- \*operating humidity: 10% to 95% RH
- \*storage temperature : 0°C to 65°C
- \*storage humidity: 5% to 95% RH

### Performance upgrade capability and relative products:

- \*A102 : PCIe card support two RS232 ports.
- \*A132: PCIe card support two RS422/RS485 ports.
- \*A112: PCIe card support two RS232/RS422/RS485 ports.
- \*A104: PCIe card support four RS232 ports.
- \*A114: PCIe card support four RS232/RS422/RS485 ports.
- \*APE8S/1(Ape168): PCIe card support eight RS232 ports.
- \*A134I: PCIe card support four Ground isolated RS422/RS485 ports.
- \*A124I: PCIe card support two RS232 and two Ground isolated RS422/RS485 ports.
  - \*\*\*All names are the trademarks of their respective organization.

#### RAYON TECHNOLOGY CO., LTD.

2F, No. 177, Chung\_Shan 2 Rd., Lu\_Chou, New Taipei city, Taiwan.,R.O.C

TEL: 886-2-82858362 FAX: 886-2-82857065

E-Mail: <u>rayon@ms1.hinet.net</u> or <u>info@rayontech.com.tw</u>

WEB: <a href="http://www.rayontech.com.tw">http://www.rayontech.com.tw</a>